

FMR-7033 LCD Keypad

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Compatible with the FPD-7024 FACP
- ▶ Two-line, 32-character, alphanumeric LCD display
- ▶ Status LEDs identify alarm, trouble, supervisory, and silenced conditions
- ▶ Address setting by jumper
- ▶ Remotely control system commands and programming

The FMR-7033 LCD Keypad combines remote annunciator and controller functions for fire alarm systems controlled by the FPD-7024 Fire Alarm Control Panel (FACP). It operates identically to the user interface on the FPD-7024 FACP. You can connect up to four FMR-7033 keypads to an FPD-7024. The FMR-7033 allows remotely starting local system tests, system programming, system control, and viewing the system's event log. Passcode protect access to system functions allowing installation in areas open to the general public. The two-line, 32-character LCD (liquid-crystal display) annunciates system status and events. The top line provides general system status information, while the bottom line identifies specific devices or instructions. An internal sounder signals alarm, supervisory, and trouble conditions and annunciates keystrokes during programming and control procedures. Four status LEDs indicate supervisory, alarm, trouble, and silenced conditions. A pull-out slide with operating instructions fits behind the mounting base.

Certifications and approvals

Region	Certification	
USA	UL	UOJZ: Control Units, System (ANSI/UL 864)
	FM	FMR-7033
	CSFM	see our website
	FDNY-CoA	#6173

Installation/configuration notes

Compatible Products

The following products are compatible with the FMR-7033 LCD Keypad:

Category	Product ID	Product Description
Control Panels	FPD-7024	FACP
Keypads and Annunciators	D7030X	LED annunciator
	D7030X-S2	LED annunciator
	D7030X-S8	LED annunciator

Mounting

Surface mount or mount the FMR-7033 on a single-gang or four-inch square back box.

Wiring Guidelines

- Do not share keypad wiring with multiplex, telephone, or notification appliance circuit (NAC) wiring.
- Use a minimum of 22 AWG (0.8 mm) four-wire cable; do not use twisted pair or shielded cable.

**Notice**

A minimum of 18 AWG (1.2 mm) cable is needed for NEC-NFPA-72.

- Do not exceed 1000 ft (305 m) between the control panel and the remote keypads.
- Do not exceed 4000 ft (1219 m) of keypad wiring per system.

Number of keypads

Do not connect more than four keypads. Place up to two keypads along any single 1000 ft (305 m) run of 22 AWG (0.8 mm) wire. Three keypads can be used on any single 1000 ft (305 m) run of 18 AWG (1.2 mm) wire.

Parts included

Quant.	Component
1	LCD keypad
1	Literature pack

Technical specifications**Enclosure Design**

Dimensions (HxWxD):	4.6 in. x 6.3 in. x 1.2 in. (12 cm x 16 cm x 3 cm)
---------------------	---

Environmental Considerations

Environment:	Indoor, dry
Relative Humidity:	Up to 95%, non-condensing
Temperature (Operating):	+32°F to +122°F (0°C to +50°C)

Power Requirements (Option Bus)

Current (alarm):	100 mA
Current (standby):	80 mA
Voltage (operating):	12 VDC nominal

Ordering information**FMR-7033 LCD Keypad**

Combines remote annunciator and controller functions for fire alarm systems controlled by the FPD-7024 Fire Alarm Control Panel

Order number **FMR-7033**

Represented by:

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com